

Архангельск (8182)63-90-72  
Астана (7172)727-132  
Астрахань (8512)99-46-04  
Барнаул (3852)73-04-60  
Белгород (4722)40-23-64  
Брянск (4832)59-03-52  
Владивосток (423)249-28-31  
Волгоград (844)278-03-48  
Вологда (8172)26-41-59  
Воронеж (473)204-51-73  
Екатеринбург (343)384-55-89  
Иваново (4932)77-34-06

Ижевск (3412)26-03-58  
Иркутск (395)279-98-46  
Казань (843)206-01-48  
Калининград (4012)72-03-81  
Калуга (4842)92-23-67  
Кемерово (3842)65-04-62  
Киров (8332)68-02-04  
Краснодар (861)203-40-90  
Красноярск (391)204-63-61  
Курск (4712)77-13-04  
Липецк (4742)52-20-81  
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13  
Москва (495)268-04-70  
Мурманск (8152)59-64-93  
Набережные Челны (8552)20-53-41  
Нижний Новгород (831)429-08-12  
Новокузнецк (3843)20-46-81  
Новосибирск (383)227-86-73  
Омск (3812)21-46-40  
Орел (4862)44-53-42  
Оренбург (3532)37-68-04  
Пенза (8412)22-31-16  
Казахстан (772)734-952-31

Пермь (342)205-81-47  
Россия (495)268-04-70  
Ростов-на-Дону (863)308-18-15  
Рязань (4912)46-61-64  
Самара (846)206-03-16  
Санкт-Петербург (812)309-46-40  
Саратов (845)249-38-78  
Севастополь (8692)22-31-93  
Симферополь (3652)67-13-56  
Смоленск (4812)29-41-54  
Сочи (862)225-72-31  
Ставрополь (8652)20-65-13

Сургут (3462)77-98-35  
Тверь (4822)63-31-35  
Томск (3822)98-41-53  
Тула (4872)74-02-29  
Тюмень (3452)66-21-18  
Ульяновск (8422)24-23-59  
Уфа (347)229-48-12  
Хабаровск (4212)92-98-04  
Челябинск (351)202-03-61  
Череповец (8202)49-02-64  
Ярославль (4852)69-52-93

<https://nuoying.nt-rt.ru/> || [nyo@nt-rt.ru](mailto:nyo@nt-rt.ru)

## Преобразователь дифференциального давления Differential pressure transmitter



### 1 Design features

High accuracy and good stability It has the functions of continuous self-diagnosis, linear compensation and digital fine-tuning.

It can adjust the zero position and range locally, and it can also adjust remotely through remote handheld terminals and computers.

Linear or square root output can be selected according to different applications.

Conversion of settable damping time between 0.1 and 16S

Conversion of pressure units between KPa, Pa, InH tamping O, bar, etc.

Failure and safety modes can be set by switching failure/safety switches

Multi-point, single-point and burst mode

With the function of power-off protection, the working data can be automatically saved when power-off occurs.

Solid Component, Plug-in Printed Circuit Board Small, Light Weight, Strong Earthquake Resistance

### 2. Technical parameters

Typical applications: liquid, gas, steam

Accuracy Level: 0.1 Level, 0.2 Level

Power supply: 24VDC (+30%)

Signal output: 4-20 mADC/HART/RS485

Ambient temperature: - 40 ~ + 85 C

Process temperature: - 25 ~ + 125 (> 125 (> customizable)

Process connection: flange

Damping time: 0.1-16s adjustable

Power supply effect: <0.005%/v

Vibration effect: <1% maximum range (10-60 HZ, S=0.07 MM; 60-150 HZ, G)

Adjustable filling fluid: silicone oil, inert oil (optional)

On-site display: LCD (optional)

Protection Level: IP65

Explosion-proof grade: Exia IIC T6, Exd IIB T5 (optional)